

DEVICE SPECIFICATIONS

NI USB-5684

10 MHz to 18 GHz RF Power Meter

This document lists specifications for the NI USB-5684 (NI 5684) RF power meter. Minimum or maximum specifications are warranted under the following conditions:

- 1 hour warm-up time at ambient temperature
- Calibration cycle maintained
- Temperature 0 °C to 50 °C unless otherwise noted

Typical values are used to define a non-warranty specification that at least 68% of units exhibit at ambient temperatures of 15 °C to 35 °C. Specifications that do not list tolerance values are typical values unless otherwise specified. Tolerance values represent the maximum variation.

Specifications are subject to change without notice. For the most recent device specifications, visit ni.com/manuals.

Contents

General.....	2
Uncertainty.....	2
Power Measurement.....	5
Continuous Mode.....	5
Scope Mode.....	6
Time Slot Mode.....	6
Trigger.....	7
Internal Trigger.....	7
Trigger In.....	7
Trigger Out.....	7
Interface.....	8
Maximum Damage Levels.....	8
DC Power Requirements (5 V) from Host USB.....	8
Calibration.....	8
Physical Characteristics.....	8
Environment.....	9
Operating Environment.....	9
Storage Environment.....	9
Shock and Vibration.....	9
Compliance and Certifications.....	10
Safety.....	10
Electromagnetic Compatibility.....	10

CE Compliance	10
Online Product Certification.....	11
Environmental Management.....	11

General

Frequency range	10 MHz to 18 GHz
Input range	-60 dBm to +20 dBm
Input VSWR	
10 MHz to <150 MHz	<1.17 : 1
150 MHz to 2 GHz	<1.12 : 1
>2 GHz to 12.4 GHz	<1.22 : 1
>12.4 GHz to 18 GHz	<1.25 : 1
Measurement range	
Range 1	+4 dBm to +20 dBm, typical
Range 2	-16 dBm to +4 dBm, typical
Range 3	-60 dBm to -16 dBm, typical
Signal-channel bandwidth	50 kHz, typical

Uncertainty

Absolute Power Measurement Uncertainty¹

Table 1. Measurement Uncertainty (dB), 0 °C to 50 °C

Power Measured (dBm)	Frequency (GHz)			
	≤0.05	>0.05 to 2	>2 to 12.4	>12.4 to 18
-60 to <-16	0.14	0.14	0.14	0.17
-16 to <+4	0.14	0.14	0.13	0.13
+4 to +20	0.14	0.15	0.15	0.14

¹ Expanded uncertainty with $k = 2$ for a CW measurement after zeroing. Includes calibration factor and linearity; noise, zero set and drift must be added.

Table 2. Measurement Uncertainty (dB), 20 °C to 30 °C

Power Measured (dBm)	Frequency (GHz)			
	≤0.05	>0.05 to 2	>2 to 12.4	>12.4 to 18
-60 to <-16	0.13	0.12	0.14	0.14
-16 to <+4	0.11	0.10	0.13	0.11
+4 to +20	0.11	0.10	0.10	0.11

Relative Power Measurement Uncertainty²**Table 3.** Measurement Uncertainty (dB), ≤0.05 GHz

Initial Power Measured (dBm)	Final Power Measured (dBm)					
	0 °C to 50 °C			20 °C to 30 °C		
	+4 to +20	-16 to <+4	-60 to <-16	+4 to +20	-16 to <+4	-60 to <-16
-60 to <-16	0.14	0.13	0.03	0.08	0.09	0.03
-16 to <+4	0.14	0.04	0.13	0.06	0.03	0.09
+4 to +20	0.05	0.14	0.14	0.05	0.06	0.08

Table 4. Measurement Uncertainty (dB), >0.05 GHz to 2 GHz

Initial Power Measured (dBm)	Final Power Measured (dBm)					
	0 °C to 50 °C			20 °C to 30 °C		
	+4 to +20	-16 to <+4	-60 to <-16	+4 to +20	-16 to <+4	-60 to <-16
-60 to <-16	0.16	0.16	0.03	0.11	0.12	0.03
-16 to <+4	0.17	0.05	0.16	0.09	0.04	0.12
+4 to +20	0.06	0.17	0.16	0.06	0.09	0.11

² Expanded uncertainty with $k = 2$ for measurement of a change in power of a CW signal after zeroing. Includes calibration factor and linearity; noise, zero set and drift must be added.

Table 5. Measurement Uncertainty (dB), >2 GHz to 12.4 GHz

Initial Power Measured (dBm)	Final Power Measured (dBm)					
	0 °C to 50 °C			20 °C to 30 °C		
	+4 to +20	-16 to <+4	-60 to <-16	+4 to +20	-16 to <+4	-60 to <-16
-60 to <-16	0.16	0.16	0.04	0.12	0.14	0.04
-16 to <+4	0.17	0.05	0.16	0.10	0.04	0.14
+4 to +20	0.06	0.17	0.16	0.07	0.10	0.12

Table 6. Measurement Uncertainty (dB), >12.4 GHz to 18 GHz

Initial Power Measured (dBm)	Final Power Measured (dBm)					
	0 °C to 50 °C			20 °C to 30 °C		
	+4 to +20	-16 to <+4	-60 to <-16	+4 to +20	-16 to <+4	-60 to <-16
-60 to <-16	0.14	0.15	0.04	0.12	0.14	0.04
-16 to <+4	0.11	0.06	0.15	0.10	0.05	0.14
+4 to +20	0.06	0.11	0.14	0.06	0.10	0.12

Table 7. Noise, Zero Set, Zero Drift Uncertainty

Power Measured (dBm)	Noise ³	Zero Set ⁴	Zero Drift ⁵
-60 to <-16	<123 pW	<332 pW	<344 pW
-16 to <+4	<10.1 nW	<38.7 nW	<42.9 nW
+4 to +20	<0.856 μW	<1.07 μW	<0.996 μW

³ Noise is specified as two-sigma (at three-sigma confidence) after zero operation when measured with 10.2 seconds of measurement time (measurement time = *Aperture Time* * *Number of Averages*). Effect of noise can be reduced by increasing the number of averages and/or increasing the aperture time. Noise decreases at a rate equal to the square root of the number of averages and aperture time.

⁴ Zero set is specified as the mean (at three-sigma confidence) after zero operation when measured with 256 averages and 40 ms aperture time for 1 hour, and when keeping the temperature within ±1 °C.

⁵ Zero drift is specified as two-sigma (at three-sigma confidence) after zero operation when measured with 256 averages and 40 ms aperture time for 1 hour, and when keeping the temperature within ±1 °C.

Table 8. Effects of Digital Modulation⁶

Power Measured (dBm)	Uncertainty (dB)
-60 to <-16	+0.080/-0.048
-16 to <+4	+0.088/-0.038
+4 to +20	+0.067/-0.055

Power Measurement

Measurement	Average power
Measurement resolution	0.01 dB maximum
Offset range	-100 dB to +150 dB
Averaging	
Averaging mode	Auto, manual
Averaging type	Moving, repeat
Number of averages (manual) ⁷	1 to 65,536
Auto-averaging	
Resolution ⁸	1 dB, 0.1 dB, 0.01 dB
Source	Time Slot mode: 1 to 128 slots; or Scope mode: 1 to 16,384 data points

Continuous Mode

Duty cycle correction	0.001% to 100%
Aperture time	0.01 ms to 1 s

⁶ Measurement error with reference to a CW signal of equal power and frequency at 20 °C to 30 °C.

⁷ Maximum number of averages allowed in Continuous mode and Time Slot mode is 65,536. In Scope mode, the maximum number of averages is equal to 16,777,216 divided by the number of data points.

⁸ Averaging resolution of 0.001 dB is not available with the NI-568x SFP. This feature is only available when using the NI-568x instrument driver. Averaging resolution is defined as the place after the decimal to which the reading becomes stable.

Maximum buffer size	8,192
Measurement time ⁹	Up to 1,000 measurements per second, unbuffered More than 10,000 measurements per second, buffered

Table 9. Measurement Time Examples

Aperture Time (ms)	Averages = 1, in ms	Averages = 10, in ms
0.01	1.0	1.5
0.1	1.2	3.0
1	4.0	19.1
10	34.6	187
100	347	1907

Scope Mode

Capture time	0.01 ms to 1 s
Data points	1 to 16,384
Resolution	0.01 ms maximum
Measurement time ¹⁰	<i>Capture Time</i> * 6.2 + 0.013

Time Slot Mode

Maximum number of slots	128
Slot width	0.01 ms to 100 ms
Maximum capture time	1,000 ms (<i>Slot Width</i> * <i>Number of Slots</i>)
Resolution	0.01 maximum

⁹ Times are typical based on benchmark results taken using an NI PXIe-8135 controller and an NI USB-5684. Performance may vary based on system configuration. Trigger source set to Immediate. Number of Averages = 1 for repeat average mode.

¹⁰ Times are typical based on benchmark results taken using an NI PXIe-8135 controller and an NI USB-5684. Performance may vary based on system configuration. Trigger source set to Immediate. Number of Averages = 1 for repeat average mode.

Exclusion periods¹¹

Start exclusion	0 ms to 10 ms
End exclusion	0 ms to 10 ms

Trigger

Internal Trigger

Source ¹²	Bus or Continuous (Auto, Single or Multiple)
Range	-35 dBm to +20 dBm
Level accuracy	±0.5 dB, typical
Slope	Positive or negative
Delay range	-5 ms to 10 s
Delay resolution	10 µs

Trigger In

Impedance	4 kΩ, nominal
Type	TTL/CMOS
Slope	Positive
Delay range	-5 ms to 10 s
Delay resolution	10 µs
Voltage high threshold	2.3 V, typical
Voltage low threshold	1.2 V, typical
Hysteresis	0.2 V, typical
Maximum voltage	±5.5 V
Minimum pulse width	100 ns
Latency ¹³	10.6 µs, maximum
Repetition period	14.2 µs, minimum

Trigger Out

Trigger Out capability is not currently implemented.

¹¹ The start exclusion time plus the end exclusion time must be less than the slot width.

¹² Software trigger not available in the NI-568x SFP. This feature is only available when using the NI-568x instrument driver. Internal and external triggers are not available when using Continuous acquisition mode.

¹³ Latency is defined as the time delay between the sensor receiving the trigger and the measurement initiation.

Interface

RF connector	N (m)
Interface to host	USB 2.0 full speed (compatible with USB 1.0 and USB 1.1)
External trigger input	MCX(f)

Maximum Damage Levels

Maximum DC voltage at RF port	±20 V
Maximum power at RF port	+30 dBm (+34 dBm for 10 µs pulse, 10% duty cycle)
Maximum voltage at trigger input	5.5 V

DC Power Requirements (5 V) from Host USB

Typical current	450 mA
-----------------	--------



Caution You can impair the protection provided by the NI 5684 if you use it in a manner not described in this document.

Calibration

Interval	1 year; calibration interval starts with the date the product is put into service by the customer
----------	---

Physical Characteristics

Dimensions	110 mm x 45 mm x 25.6 mm, excluding RF connector and silicone cover
Weight	397 g (0.88 lb)



Caution Clean the hardware with a soft, nonmetallic brush. Make sure the hardware is completely dry and free from contaminants before returning it to service.

Environment

Maximum altitude	4,600 m operational
Pollution Degree	2

Indoor use only.

Operating Environment

Ambient temperature range	0 °C to 50 °C (Tested in accordance with IEC 60068-2-1 and IEC 60068-2-2.)
Relative humidity range ¹⁴ (noncondensing)	
At 50 °C	45%
At 40 °C	75%
At 30 °C	95%

Storage Environment

Ambient temperature range	-40 °C to +71 °C (Tested in accordance with MIL-PRF-28800F (Class 3).)
Relative humidity range	5% to 95%, noncondensing (Tested in accordance with MIL-PRF-28800F (Class 3).)

Shock and Vibration

Operating shock	30 g peak, half-sine, 11 ms pulse (Tested in accordance with IEC 60068-2-27. Meets MIL-PRF-28800F Class 2 limits.)
Random vibration	
Operating	5 Hz to 500 Hz, 0.3 g _{rms}
Nonoperating	5 Hz to 500 Hz, 2.4 g _{rms} (Tested in accordance with IEC 60068-2-64. Nonoperating test profile exceeds the requirements of MIL-PRF-28800F, Class 3.)

¹⁴ Tested in accordance with IEC 60068-2-56.

Compliance and Certifications

Safety

This product is designed to meet the requirements of the following electrical equipment safety standards for measurement, control, and laboratory use:

- IEC 61010-1, EN 61010-1
- UL 61010-1, CSA 61010-1



Note For UL and other safety certifications, refer to the product label or the [Online Product Certification](#) section.

Electromagnetic Compatibility

This product meets the requirements of the following EMC standards for electrical equipment for measurement, control, and laboratory use:

- EN 61326-1 (IEC 61326-1): Class A emissions; Basic immunity
- EN 55011 (CISPR 11): Group 1, Class A emissions
- EN 55022 (CISPR 22): Class A emissions
- EN 55024 (CISPR 24): Immunity
- AS/NZS CISPR 11: Group 1, Class A emissions
- AS/NZS CISPR 22: Class A emissions
- FCC 47 CFR Part 15B: Class A emissions
- ICES-001: Class A emissions



Note In the United States (per FCC 47 CFR), Class A equipment is intended for use in commercial, light-industrial, and heavy-industrial locations. In Europe, Canada, Australia, and New Zealand (per CISPR 11), Class A equipment is intended for use only in heavy-industrial locations.



Note Group 1 equipment (per CISPR 11) is any industrial, scientific, or medical equipment that does not intentionally generate radio frequency energy for the treatment of material or inspection/analysis purposes.



Note For EMC declarations, certifications, and additional information, refer to the [Online Product Certification](#) section.

CE Compliance

This product meets the essential requirements of applicable European Directives, as follows:

- 2014/35/EU; Low-Voltage Directive (safety)
- 2014/30/EU; Electromagnetic Compatibility Directive (EMC)

Online Product Certification

Refer to the product Declaration of Conformity (DoC) for additional regulatory compliance information. To obtain product certifications and the DoC for this product, visit ni.com/certification, search by model number or product line, and click the appropriate link in the Certification column.

Environmental Management

NI is committed to designing and manufacturing products in an environmentally responsible manner. NI recognizes that eliminating certain hazardous substances from our products is beneficial to the environment and to NI customers.

For additional environmental information, refer to the *Minimize Our Environmental Impact* web page at ni.com/environment. This page contains the environmental regulations and directives with which NI complies, as well as other environmental information not included in this document.

Waste Electrical and Electronic Equipment (WEEE)



EU Customers At the end of the product life cycle, all NI products must be disposed of according to local laws and regulations. For more information about how to recycle NI products in your region, visit ni.com/environment/weee.

电子信息产品污染控制管理办法（中国 RoHS）



中国客户 National Instruments 符合中国电子信息产品中限制使用某些有害物质指令 (RoHS)。关于 National Instruments 中国 RoHS 合规性信息，请登录 ni.com/environment/rohs_china。(For information about China RoHS compliance, go to ni.com/environment/rohs_china.)

Refer to the *NI Trademarks and Logo Guidelines* at ni.com/trademarks for information on National Instruments trademarks. Other product and company names mentioned herein are trademarks or trade names of their respective companies. For patents covering National Instruments products/technology, refer to the appropriate location: **Help»Patents** in your software, the `patents.txt` file on your media, or the *National Instruments Patent Notice* at ni.com/patents. You can find information about end-user license agreements (EULAs) and third-party legal notices in the readme file for your NI product. Refer to the *Export Compliance Information* at ni.com/legal/export-compliance for the National Instruments global trade compliance policy and how to obtain relevant HTS codes, ECCNs, and other import/export data. NI MAKES NO EXPRESS OR IMPLIED WARRANTIES AS TO THE ACCURACY OF THE INFORMATION CONTAINED HEREIN AND SHALL NOT BE LIABLE FOR ANY ERRORS.

U.S. Government Customers: The data contained in this manual was developed at private expense and is subject to the applicable limited rights and restricted data rights as set forth in FAR 52.227-14, DFAR 252.227-7014, and DFAR 252.227-7015.