

**INGCO Auto Ranging Digital Clamp Meter TRMS 6000 Counts
DCM6005**

DC Current: 60A/600A ± (2.5%+5)
AC Current: 60A/600A ± (2.5%+5)
AC Voltage: 6V/60V/600V ± (0.8%+5)
DC Voltage: 600mV/6V/60V/600V± (0.5%+5)
Resistance: 600Ω/6kΩ/60kΩ/600kΩ/6MΩ/60MΩ ± (1.0%+5)
Capacitance: 10nf/100nf/1000nf/10μF/100μF/1000μF/10mf/100mf ± (4.0%+5)
Frequency: 10Hz/100Hz/1000Hz/10KHz/100KHz/1000KHz± (1.0%+3)
10MHz± (3.0%+3)
Duty cycle: 1%~99% ± (3.0%+3)
Temperature: -20~1000°C(-4~1832°F)



Product Specifications

Color	Black
Ean	6925582147896
Included Components	AC/DC clamp meter; 2pcs batteries; test leads
Item Weight	14.9 ounces
Measurement Type	Multimeter
Number of Items	1
Part Number	DCM6005
Size	AC/DC Clamp Meter
Specification Met	
Style	AC/DC Clamp Meter

<https://www.amazon.com/Ingco-6005OLDNEW/dp/B08FD9Q1Q5?th=1>